



## Trijicon® RMR® Quick Reference Card

**Power on:** Press either button to turn on. RMR wakes up in automatic mode.

**Press both buttons** simultaneously for less than 3 seconds and release to enter automatic mode. Press both buttons simultaneously and hold them for 3 seconds **to turn the unit off.**

Press and release the **plus button** to increase brightness and enter manual mode. Press and release the **minus button** to decrease brightness and enter manual mode.


Aiming dot automatically adjusts to ambient lighting after **16.5 hours.**

qrc\_rmr\_v6.odg

RJJ 20210702

1 IN

## Trijicon® RMR® Quick Reference Card



**Manual illumination** control has 8 brightness settings.

**Automatic mode** covers settings 3-7 depending on ambient light.

Battery is a CR2032 3V DC Lithium. Install negative side "-" facing down.

The aiming dot will become dimmer as the battery gets low.

Turn **Adjustment screws** in the direction to move impacts, 1click=1MOA

**25 yds:** 6.5 MOA=1.7" / 3.25 MOA=0.9"

**10 yds:** 6.5 MOA=0.7", 3.25 MOA=0.3"

Torque Optic Screws until seated, then secure.

Clean with fresh water and clean cloth, not alcohol, TCE or acetone

Trijicon Customer Service: [www.trijicon.com](http://www.trijicon.com) (800) 338-0563

1 CM